

CAP-REX-1G

EXIT BUTTON

Contactless Request To Exit Button



Key Features

- When triggered, the back light will change colour with an audible tone
- Provides a dry contact output to interface with any access control controller
- Built-in mechanical override in case of power failure or electronic failure
- Built-in a digital timer to control the relay output timing from 1 to 15 sec
- Back lit design and built-in buzzer (buzzer selectable)
- Capacitance proximity technology has been used instead of infrared technology – environmental independent design

The Genie **CAP-REX-1G** is a sleek contactless request to exit button and works using capacitive technology. It has a blue LED back light which turns green on activation.

The **CAP-REX-1G** is 1G in size making it perfect for most access control applications.



Specification

Request To Exit Indication	Colour changes from Blue to Green with a beep
Request To Exit Output	Dry contact output
REX Relay	NC / NO jumper selectable rated @ DC30V, 1A
Mechanical Override	Available
Output Timer	From 1 sec to 15 sec
Typical Read Range	~2.5 cm
Operating Voltage	DC12-24V
Operating Current	150mA (Max. @ DC12V)
Operating Temperature	-20°C ~ +60°C
Operating Humidity	10% - 90% RH
Case	PC, ABS (Black and white colour)
Dimensions	92 × 92 × 8.5 mm

Dimensions

